# Inductive sensor
# Ni10-M18-Y1X-H1141

Industrial Automation




- **ATEX category II 1 G, Ex zone 0**
- **ATEX category II 1 D, Ex zone 20**
- **SIL2 as per IEC 61508**
- **Threaded barrel, M18 x 1**
- **Chrome-plated brass**
- **2-wire DC, nom. 8.2 VDC**
- **output according to DIN EN 60947-5-6 (NAMUR)**
- **connector M12 x 1**

### Wiring diagram




| | |
|---|---|
| **Type** | Ni10-M18-Y1X-H1141 |
| Ident-No. | 40153 |
| **Rated operating distance Sn** | 10 mm |
| Mounting condition | non-flush |
| Assured sensing range | (0,81 x Sn) mm |
| Correction factors | St37 = 1, V2A ~ 0.7, Ms ~ 0.4, Al ~ 0.3 |
| Repeatability | 2 % |
| Temperature drift | ± 10 % |
| Hysteresis | 1… 10 % |
| Ambient temperature | -25…+ 70 °C |
| **Output function** | 2-wire, NAMUR |
| Switching frequency | 0.5 kHz |
| Voltage | Nom. 8.2 VDC |
| Non-actuated current consumption | ≥ 2.1 mA |
| Actuated current consumption | 1.2 mA |
| **Approval acc. to** | KEMA 02 ATEX 1090X issue no.: 3 |
| Internal inductance ($L_i$) / capacitance ($C_i$) | 150 nF / 150 µH |
| Device designation | Ex II 1 G Ex ia IIC T4/II 1 D Ex ia D 20 T115 °C (max. $U_i$ = 20 V, $I_i$ = 20 mA, $P_i$ = 200 mW) |
| **Housing** | threaded barrel, M18 x 1 |
| Dimensions | 52 mm |
| Housing material | metal, CuZn, chrome-plated |
| Material active face | plastic, PBT |
| Tightening torque of housing nut | 25 Nm |
| Connection | connectors, M12 x 1 |
| Vibration resistance | 55 Hz (1 mm) |
| Shock resistance | 30g (11 ms) |
| Degree of protection | IP67 |
| **Display switch state** | LED yellow |

### Functional principle

Inductive sensors are designed for wear-free and non-contact detection of metal objects. For this purpose they use a high-frequency electro-magnetic AC field that interacts with the target. Conserning inductive sensors, this field is generated by an LC resonant circuit with a ferrite core coil.

• Edition: • 08.11.2008

Casp System Sp. Z o.o., Puszkina 2, 43-603 Jaworzno, Polska, www.casp.pl, e-mail: biuro@casp.pl, tel/fax: +48 32 614 09 17

# Inductive sensor
# Ni10-M18-Y1X-H1141

| | |
|---|---|
| **Mounting instructions** | minimum distances |
| Distance D | 3 x B |
| Distance W | 3 x Sn |
| Distance T | 3 x B |
| Distance S | 1,5 x B |
| Distance G | 6 x Sn |
| Distance N | 2 x Sn |
| **Diameter of the active area B** | Ø 18 mm |




• Edition: • 08.11.2008

Industrial Automation

## Accessories

| Type code | Ident-No. | Short text | Dimension drawing |
|---|---|---|---|
| IM1-22EX-R | 7541231 | Isolating switching amplifier, 2 channel; 2 transistor outputs; input for NAMUR signals; selectable ON/OFF mode for wire-break and short-circuit monitoring; adjustable signal flow (N.O./ N.C.mode); removable terminal blocks; 18 mm width; universal voltage supply unit |  |
| BST-18B | 6947214 | fixing clamp with dead-stop; material: PA6 |  |
| QM-18 | 6945102 | quick-mount fixing clamp with dead-stop; material: chrome-plated brass male thread M24 x 1.5. Note: The switching distance of proximity switches can be reduced by the use of quick mounting brackets. |  |
| MW-18 | 6945004 | mounting bracket; material: stainless steel A2 1.4301 (AISI 304) |  |
| BSS-18 | 6901320 | fixing clamp; material: polypropylene |  |

• Edition: • 08.11.2008

# Inductive sensor
# Ni10-M18-Y1X-H1141

Industrial Automation

## Operating manual

### Intended usage

This device fulfils the directive 94/9/EC and is suited for use in explosion hazardous areas according to EN60079-0, -11, -26 and EN61241-0, -11 Further it is suited for use in safety-related systems, including SIL2 as per IEC 61508. In order to ensure correct operation to the intended purpose it is required to observe the national regulations and directives.

### For use in explosion hazardous areas conform to classification

II 1 G and II 1 D (Group II, Category 1 G, electrical equipment for gaseous atmospheres and category 1 D, electrical equipment for dust atmospheres).

### Marking (see device or technical data sheet)

Ⓔx II 1 G and Ex ia IIC T6 as per EN60079-11 and -26 and Ⓔx II 1 D Ex iaD 20 T 115°C as per EN60079-11 and EN61241-0 and -11

### Local admissible ambient temperature

-25…+70 °C

### Installation / Commissioning

These devices may only be installed, connected and operated by trained and qualified staff. Qualified staff must have knowledge of protection classes, directives and regulations concerning electrical equipment designed for use in explosion hazardous areas. Please verify that the classification and the marking on the device comply with the actual application conditions.

This device is only suited for connection to approved Exi circuits compliant to EN60079-0 and -11. Please observe the maximum admissible electrical values. After connection to other circuits the sensor may no longer be used in Exi installations. When interconnected to (associated) electrical equipment, it is required to perform the "Proof of intrinsic safety" (EN60079-14). When employed in safety systems to IEC 51408 it is required to assess the failure probability (PFD) of the complete circuitry.

### Installation and mounting instructions

Avoid static charging of cables and plastic devices. Please only clean the device with a damp cloth. Do not install the device in a dust flow and avoid build-up of dust deposits on the device. If the devices and the cable could be subject to mechanical damage, they must be protected accordingly. They must also be shielded against strong electro-magnetic fields. The pin configuration and the electrical specifications can be taken from the device marking or the technical data sheet.

### Repair / maintenance

Repairs are not possible. The approval expires if the device is repaired or modified by a person other than the manufacturer. The most important data from the approval are listed.

• Edition: • 08.11.2008